

### 800 Series Motor Chart

<u>Model No.</u>	<u>Serial No.</u>	<u>Motor No.</u>
823	# starts w/ 9775 (2 V belts) (1 flat ribbed belt)	823-00048 823-00048-R
823E	ALL	823-00048-R
825	# starts w/ 9775 (2 V belts) (1 flat ribbed belt)	NLA 825-00048-N
825E	ALL	823-00048-R
825A	ALL	825-00048-R
827	2 V-belts 1 flat ribbed belt	827-00048 827A-00048
827E	ALL	825-00048-N
827A	# < 37335 USE: # ≥ 37335 USE:	827A-00048 827A-00048-N
829E	# < 60361 USE: # ≥ 60361 USE:	829-00048 829E-00048
829A	ALL	829-00048
839A	ALL	829-00048